OS11A-1113

Coastal retracking using along-track echograms and its dependency on coastal topography

Kaoru Ichikawa ichikawa@riam.kyushu-u.ac.jp
(RIAM, Kyushu Univ., Japan)

XiFeng Wang
(Dalian Ocean Univ., China)

Research Institute for Applied Mechanics, Kyushu University
九州大学応用力学研究所

1. Introduction

Coastal ALT waveform (*i.e.* time-series of echo intensity) are often contaminated by
- ⊗weaker reflections by lands
- ⊗stronger reflections by calm water surface in semi-closed bays or ports

The latter may cause failure of detection of the leading edge, and thus the range measurements (Fig.1).



Fig.1 Example of contaminated waveform (right), which was measured at the location shown in the map (left). Small bays (yellow and green stars) cause pseudo leading edges in the waveform.

Several ***coastal retrackers*** have been developed; most of them are ***sub-waveform retrackers*** which avoild use of the trailing edge that might be contaminated (*e.g.* ALES).

In this study, a new retracker is proposed that uses ***along-track echograms***, *i.e.*, sequential waveforms along a track (Fig. 2). Unlike other retrackers, contaminations in a waveform can be detected by refering ***neighbor waveforms*** (Wang and Ichikawa, 2017).

In general, the present new post-processing along-track method performs better than the other single-point retrackers, and thus the SSH can be retrieved closer to the shoreline. However, its improvement strongly depends on the coastal topography. In this presentation, the results are compared in three locations with different topography.



Fig.2 Example of an echogram along the same track as in Fig. 1. The echo power intensity (color contours) along 34.2N (red broken line) shows the same variations as the waveform in Fig.1.

2. Data

The 20 Hz along-track waveform of Jason-2 in Sendor Geophysical Data Record (S-GDR) are used for Cycle 1-252 (2008.7-2015.4; AVISO).

For comparison, Adaptive Leading Edge Subwaveform (ALES) Jason-2 coastal altimetry product (Passaro *et al.*, 2014) are used (http://www.coastalt.eu/community), in addition to the traditional S-GDR retracking algorithm for open oceans.

Tracks #36 (across Tsushima Island, Japan) and #164 (across Taiwan) are selected for locations with different topography (Fig. 3). The area south of Tsushima Island (red rectangle in Fig.3) is first discussed in Section 4.1, comparing with tide gauge record at *Izuhara*. Then the northern area (blue rectangle) and the south of Taiwan (yellow rectangle) are compared in Sections 4.2 and 4.3, respectively.



Fig.3 Jason-2 descending tracks #36 and #164 (middele panel; *Google*). The track #36 passes the Tsushima Island located in the Tsushima Strait between Japan and Korea (right panel), and the track #164 passes Taiwan (left panel). Circles with the 10-km radius are plotted for reference.

Izuhara tide gauge station

3. Retracking Algorithms

3.1 Removal of bright parabolas

Since the geometry between a bright reflector on the sea surface and a satellite altimeter (Fig. 4) results in a fixed-shape parabola in the along-track echogram, the parabolic shapes are fitted recursively for all bright echos in along-track echograms.

By removing these parabolas, waveforms without contaminations can be obtained, to which the theoretical Brown waveform can be fitted (Fig. 5).



Fig.4 Schematic showing the geometrical relationship between an altimeter and a bright reflector on the sea surface. The altimeter is closest at latitude y0 with a distance d0.



Fig.5 The same along-track echogram in Fig.2 but after removal of the bright parabolas (left). In this case, five parabolas were removed.The waveform at 34.2N (right) contains no "pseudo leading edges" seen in Fig.1.

3.2 Compensation for land echo losses

Assuming that the reflected ALT signals from lands are neglegible w.r.t. these from the sea, we enhance the echo intensity by the ratio of the land area in a co-range circle (Fig. 6). This procedure significantly changes the tailing edge, so that estimations of the wind speed (or sigma-0) and Significant Wave Height (SWH) are influenced. Meanwhile, its influence on the SSH is less than 10 cm in the root-mean-squared difference (RMSD).



Fig.6 Witin the given co-range circle, the length ratio of the arcs over lands (red curve) is determined from the high-resolution coastline data (Wessel and Smith, 1996; left panel). The echo intensity is compensated based on this ratio (right panel). The slope of the trailing edge (*i.e.*, antenna mispointing angle) becomes small.

4. Area Dependency

4.1 South of Tsushima Island

The SSHAs from the 252-cycle mean are calculated for traditional SGDR and ALES products and for the present method. All extreme outliers (larger than 100m or smaller than -130m) are removed.

The correlation coefficient (CC) and RMSD with the tide gauge record at *Izuhara* indicate that the SSHA is available at a point **10 km** away from the shoreline for the traditional **SGDR**, **7 km away for ALES** and only **3 km away for this study** (Fig 7).

Time series of the SSHA at 34.21N (Fig. 8), *i.e.* 5 km away from the shoreline, shows that ALES retrieves correct SSHA, except several intermittent extreme cycles. Presence of these extreme cycles can be identified by the RMS (or, the standard deviation) of the SSHA at a point, which is used as a simple performance index in the next subsections.



Fig.7 The correlation coefficient (top) and RMSD (bottom) with the Izuhara tide gauge SSHA for the traditional SGDR (black), ALES (blue) and this study (red). The distance to the shoreline are plotted at the top.



Fig.8 Time series of the SSHA at 34.21N for tide gauge (green), ALES (blue) and this study (red).

4.2 North of Tsushima Island

In the north of Tsushima Island, the approach distance to the shoreline becomes **13 km** for **SGDR**, and **7 km** for **ALES** and **this method** (Fig. 9).

Bright parabolas from *Mine Bay* (Fig. 10), whose apex locates at 34.41N, affect only the SGDR retracker. However, contaminations from *Asou Bay* affects all retrackers.



Fig.9 The RMS of the SSHA for the traditional SGDR (black), ALES (blue) and this study (red) in the area north of Tsushima Island.



Fig.10 The locations of the Jason-2 track and bays north of Tsushima Island (left panel) and an example of the along-track echogram (cycle 22; right panel).

4.3 South of Taiwan

As shown in Fig.3, the shoreline in this study area is smooth w.r.t. Tsushima Island. No significant bright parabola is included in the along-track echograms.

In this case, the approach distance becomes **2 km** for **SGDR**, **5 km** for **ALES** and **3 km** for **this method** (Fig. 11). Performance of the sub-waveform retracker becomes rather worse in this smooth-coast case.



Fig.11 The RMS of the SSHA for the traditional SGDR (black), ALES (blue) and this study (red) in the area south of Taiwan.

5. Discussion and Summary

The new coastal post-processing retracker is proposed that uses along-track echograms. Since it can refer adjacent points in eliminating contaminated echos in waveforms, its performance is bettern than those of single-point retrackers.

The SSH can be retrieved as close as **3 km from the shoreline**, even semi-closed bays are present at off-track locations. On-track bays, however, contaminate waveform near the leading edge, and thus no retrackers works correctly.

References

Passaro *et al.* (2014) *Rem. Sen. Env.*, **145**, 173-189, 10.1016/j.res.2014.02.008.

Wang and Ichikawa (2017) *Rem. Sens.*, **9**, 762, doi:10.3390/rs9070762.

Wessel and Smith (1996) *J.G.R.*, **101**(B4), 8741-8743.